

UPDATE LEDGER NANO X FIRMWARE

Last updated: January 10, 2023


The update to firmware version 2.0.2 features a faster Bluetooth transfer rate, as well as several user experience improvements, an update to the user interface, and some bug fixes. Please read the [release notes](#) for more details about this update. Check our [troubleshooting article](#) if you need help.

Before you start

- Make sure you have updated Ledger Live through the notification banner or downloaded the [latest version of Ledger Live](#).
- Make sure your 24-word recovery phrase is available, as a precaution.
- Applications on your device will be automatically reinstalled after the update.


Ledger Live Desktop or Ledger Live Mobile

1. Start Ledger Live and go to My Ledger.
 - Click on **My Ledger** on the main menu.
 - Connect and unlock your device.
 - If asked, allow My Ledger on your device.
2. Start the firmware update.
 - Click on **Update firmware** in the orange notification banner.
If you don't see the notification banner, please try again later as the release is rolled out progressively.




- Carefully read all instructions on the window that appears.
- If your recovery phrase is written down and accessible, tick the checkbox at the bottom and click on **Continue**. The update process normally does not require the recovery phrase, but you should have it available as a precaution. [Don't have your recovery phrase?](#)


- The update will be downloaded while your device displays **Processing**.



- Your device will then display **New firmware** and the **version** number.
 - Press the right button to select **Confirm update**. Press both buttons to confirm.
 - Enter your PIN code to confirm. Your device will then restart and install the update. If you have canceled the update, please reload My Ledger to reinstall the applications.
- The update process will continue automatically.
 - Your Ledger Nano X displays **Processing**.
 - **Never** disconnect your device at this stage.



- Your device is successfully updated once Ledger Live displays **Firmware updated** and your Ledger Nano X asks for your PIN code.



- Your applications will be reinstalled automatically after you have entered your PIN code.
- *(optional)* Rename your device. If you have manually chosen a device name, this name does not persist after a firmware update. The name will be reset to the factory name: Nano X ****.

Need help?

Please check the [update troubleshooting article](#).

Did your device reset?

If your device displays **Welcome to Ledger Nano X**, it has been reset. **Don't worry**, your crypto assets are safe as long as you have your 24-word recovery phrase. Please follow the instructions to [restore your private keys](#) from your recovery phrase.

Bluetooth pairing issues

If you're experiencing Bluetooth issues after updating to firmware version 1.2.4-5, please remove the pairing and forget the Ledger Nano X on your phone. Then try the pairing again. For more information, refer to the [Fix Bluetooth issues](#) article.